

GLC-LX-SMD-SY

1000BASE-LX SFP, 1310 nm, 10 km SMF TRANSCEIVER

1. FEATURES AND SPECIFICATIONS

- ▶ Form Factor: **SFP**
- ▶ Operating Data Rate: **1G**
- ▶ Protocol(s): **GE, FC**
- ▶ Fiber Type: **SMF**
- ▶ Technique: **LX**
- ▶ Lane Count: **1**
- ▶ Wavelength(s)/Channel(s): **1310 nm**
- ▶ Nominal Distance: **10 km**
- ▶ Nominal Power Budget: **13 dB**
- ▶ Connector: **LC duplex**
- ▶ Temperature Range: **0 to +70°C, -40 to +85°C**
- ▶ Compliance: **SFP MSA, SFF-8472**
- ▶ Monitoring: **Digital diagnostic monitor interface**
- ▶ Laser Type: **FP**
- ▶ Receiver Type: **PIN**
- ▶ Power Dissipation: **1 W**

2. ABSOLUTE CHARACTERISTICS

PARAMETER	SYMBOL	MIN.	TYP.	MAX.	UNIT
SIGNAL INPUT VOLTAGE	V_{IN}	0.4	-	1.8	V
POWER SUPPLY VOLTAGE	V_{CC}	-0.5	-	4.5	V
OPERATING TEMPERATURE	T_{CASE}	0	-	+70	°C
STORAGE TEMPERATURE	T_S	-40	-	+85	°C

3. ELECTRICAL OPERATING CONDITIONS

PARAMETER	SYMBOL	MIN.	TYP.	MAX.	UNIT
SUPPLY CURRENT	I_{CC}	-	-	0.3	A
SUPPLY VOLTAGE	V_{CC}	3.13	3.3	3.47	V

4. OPTICAL CHARACTERISTICS

RECEIVER

PARAMETER	SYMBOL	MIN.	TYP.	MAX.	UNIT
OPTICAL WAVELENGTH	λ_C	1260	-	1580	nm
LOS HYSTERESIS	LOS_H	1	-	4	dB
LOS ASSERT	LOS_A	-30	-	-	dBm
LOS DE-ASSERT	LOS_D	-	-	-24	dBm
RX MAX. SENSITIVITY	P_{MIN}	-	-	-22	dBm
DAMAGE THRESHOLD	P_{MAX}	-3	-	-	dBm

TRANSMITTER

PARAMETER	SYMBOL	MIN.	TYP.	MAX.	UNIT
OPTICAL WAVELENGTH	λ_C	1260	1310	1360	nm
OPTICAL EXTINCTION RATIO	ER	9	-	-	dB
SIDE MODE SUPPRESSION RATIO	SMSR	30	-	-	dBm
SPECTRAL WIDTH	$\Delta\lambda$	-	-	4	dBm
OPTICAL TRANSMIT POWER	P_{OUT}	-9	-	-3	dBm

5. ORDERING INFORMATION

PART NAME	DESCRIPTION
GLC-LX-SMD-SY	1000Base LX SFP, 1310 nm, 10 km over SMF, LC duplex, speeddy
GLC-LX-SMD-I-SY	1000Base LX SFP, 1310 nm, 10 km over SMF, LC duplex, Industrial temperature -40 to +85°C, speeddy

6. COMPATIBILITY

A10NETWORKS (AXSK-CSFP-LR), ABB (3BSE080219R1), ACCEDIAN NETWORKS (7SN-000), ACTELIS (506R00002), ADTRAN (1184561PG1), ADVA (0061001011, 0061003008, 0061705824, 1061705850-02), ADVANTECH (SFP-GLX/LC-10E), AEROHIVE NETWORKS (AH-ACC-SFP-1G-LX), ALCATEL-LUCENT ENT. (SFP-GIG-LX), ALLIED TELESIS (AT-SPLX10), ALLNET (ALL4751), ARISTA NETWORKS (SFP-1G-LX), ARRIS (728965), ARUBA NETWORKS (JW087A), ARUBA NETWORKS/HP NETWORK (J4859C, J4859D), AUDIOCODES (SFP-LX), AVAYA/NORTEL (AA1419049-E6), AXIS (T8611), BARNFIND (BTSFP-LX-SM-0220), BAROX (AC-SFP-LX-E-10), BARRACUDA NETWORKS (SFP-LX), BINTEC (SFP-LC-TX/LX/LH), BLACKBOX (LFP413), BROADCOM (SFP-LX), BROCADE (E1MG-LX-OM), BROCADE/RUCKUS (E1MG-LX-OM), CALIX (100-01662), CENTEC (SFP-LX), CERAGON (ER-1002-0), CHECK POINT (CPAC-TR-1LX), CHELSIO (SM1G-LX), CIENA (XCVR-010M31), CIENA/NORTEL (NTTP01CF, NTTP06CFE6), CISCO SYSTEMS (GLC-LH-SM, GLC-LH-SMD, SFP-GE-L), CISCO SYSTEMS/LINKSYS (MGBLX1), CISCO SYSTEMS/VIPTELA (VIP-SFP-1GE-LX), CISCO/MERAKI (MA-SFP-1GB-LX10), CITRIX NETSCALER (EW3D0000712), CLAVISTER (CLA-APP-SFP-1G-LX), COMNET (SFP-6), CORIANT/TELLABS (0410-0448), CTC UNION (ISFP-S7020-31-D), CUMULUS NETWORKS (SFP-LX), CYAN (280-0030-00), DELL (320-2879, 320-2880, 331-5309, 407-10588, 407-BBOO), DELL/FORCE10 (GP-SFP2-1Y), DELOCK (86189), DIGITUS (DN-81001), D-LINK (DEM-310GT), DRAYTEK (SFP.DLC.212.10), ECI (OTGBE-LX), EDGE CORE (ET4202-LX), EKS ENGEL (SFP-1G-LX), ERICSSON (RDH10247/2, RDH90120/D0210, RDH90199/1), EXTREME (10052, 10060), EXTREME/ENTERASYS (MGBIC-LC09), F5 NETWORKS (OPT-0011), FIBROLAN (SF1G-LX1), FIREEYE (LX1GPX-HW), FLUKE NETWORKS (SFP-1000LX), FORCEPOINT (MOD-SFP-GE-LX10), FORTINET (FG-TRAN-LX, FN-TRAN-LX), GENBAND (SFP-LX), GIGAMON (SFP-503A1G1310), H3C/3COM (3CSFP92), HILLSTONE (TRAN-LX), HIRSCHMANN (M-SFP-LX/LC), HP H3C (JD119B, JD494A), HUAWEI (34060473, ESFP-1310NM-1000BASE-LX, ESFP-GE-LX-SM1310, OSG010N05), INFINERA/TRANSMODE (TRX100075), INTEL (SFP-LX), JUNIPER (EX-SFP-1GE-LX, NS-SFP-1GE-LX, NS-SYS-GBIC-MLX, QFX-SFP-1GE-LX, SFP-1GE-LX, SRX-SFP-1GE-LX), JUNIPER/BTI SYSTEMS (BP3AM1MI), KEYSIGHT (37973010), KEYSIGHT/IXIA (SM1310), KORENIX (SFPGLX10D), KTI NETWORKS (SFP-GLS-10-A), KVM-TEC (KT-7010), LANCOM (SFP-LX-LC1), LAW0 (981/60-20), LENOVO/BLADE NETWORK (BN-CKM-S-LX), LENOVO/IBM (90Y9424), LEVELONE (SFP-3211), LONGSHINE (LCS-MGBIC-LX-10), MARCONI (SU57AE), MCAFEE (ITV-2MLG-NA-100A), MIKROTIK (S-31DLC20D), MOTOROLA (525893-001-00, NX-7500-SFP-LX), MOXA (SFP-1GLXLC), MRV (SFP-GD-LX-R), MSA (GLC-LH-SMD), NAPATECH (802-0003-00-01), NEC (B02035-WON42), NET INSIGHT (NPA0012-L101), NETGEAR (AGM732F), NETONIX (SFP-LX), NETOPTICS (SFPKT-LX), NETSCOUT (SFP-1000LX), NEVION (SFP-TR1-13T-LR), NEXANS (88645870, 88646016), NIVEO (NVSM550U), NOKIA NETWORKS FOSC (471880A.101), NOKIA SIEMENS NETWORKS (V50017-U363-K500, V50017-U463-K500), NOKIA/ALCATEL-LUCENT (1AB376720002, 3FE25774AA01, 3HE00028AA, 3HE00028CA, 3HE00070AA), NOKIA-SIEMENS/ATRICA (AT10006-ID-R), NORTEL/JUNIPER/NSN (SFP-LX), NOVIFLOW (400000505, 400000507), NVIDIA/MELLANOX (MC3208011-LX), OMNITRON (7207-1), OPENGear (569025), ORCKIT-CORRIGENT (YTR00096), OVERTURE (3000-042), PACKETLIGHT (SL6), PAKEDGE (FM-1G-SM), PALO ALTO NETWORKS (PAN-SFP-LX), PBN (SFP-LX), PENGUIN COMPUTING (SFP-LX), PERLE (PSFP-1000D-S2LC10), PLANET (MGB-LX), RAD (SFP-6D), RADWARE (9062066), RAISECOM (USFP-GB/S32-DL), REDBACK (SFP-GE-LX), REDLION (NTSFP-LX-10), RIEDEL (1090004), ROCKWELL (1783-SFP1GLX), SANDVINE (100-00157), SIEMENS (SFP992-1LD), SOLARFLARE (SFP-LX), SONICWALL (01-SSC-9790), SOPHOS (ASG0000LX, ITFZTCHLX), STARTECH (SFP1000LHST), STORMSHIELD (NA-TRANS-SFP-LX), SYNOLOGY (SFP-LX), TELCO SYSTEMS (BTI-MGBIC-GLX-DD-LC), TELESTE (MSG211A), TP-LINK (TL-SM311LS), TRANSITION NETWORKS (TN-SFP-LX), TRENDNET (TEG-MGBS10), TURRIS OMNIA (SFP-LX), UBIQUITI NETWORKS (UF-SM-1G-S), VIAVI/JDSU (CSFP-2G-3-1), VOLKTEK (GBM-104-10), WATCHGUARD (WG8585-LX), WAYSTREAM/PACKETFRONT (SFP-1000BASE-LX-M), WESTERMO (1100-0141, 1100-0541), WINYAO (WY-1.25GB-SFP-1310NM), WI-TEK (WI-SFP10-20KM), XTERA COMMUNICATIONS (900-0092-01), YAMAHA (SFP-SWRG-LX), ZHONE (SFP-GE-LX-1310), ZTE (SFP-GE-S10K), ZYXEL (SFP-LX-10-D)

7. WARNINGS AND SECURITY INFORMATION



CAUTION: Class 1 visible laser radiation present. Long term viewing of the laser can be harmful to the human eye.



This equipment has been tested according to European legislation and has been found safe, non-intervening with other electronic devices and is not subject to interference from other electronic devices



Hazardous Goods; our products are fully compliant with Directive 2011/65/EU (RoHS II) and 2002/95 EC (RoHS I)

Laser Class 1

Our products comply with 21 CFR 1040.10 and 1040.11, except for deviations pursuant to Laser Notice No. 50, dated June 24, 2007



Only (dis)connect the transceivers in an ESD Protected Area while using certified equipment and taking all necessary precautions as specified in IEC 61340-5-1.

8. DISCLAIMER AND LEGAL NOTICES

Speeddy makes no warranties or representations, expressed or implied, of any kind relative to the information or any portion thereof contained in this document or its adaptation or use, and assumes no responsibility or liability of any kind, including, but not limited to, indirect, special, consequential or incidental damages, for any errors or inaccuracies contained in the information or arising from the adaptation or use of the information or any portion thereof. The information in this document is subject to change without notice. Speeddy and the Speeddy logo are registered trademarks of renewtech B.V. All other trademarks are acknowledged as registered trademarks and proprietary to their respective owners. Copyright © 2023 renewtech B.V., Dutch Chamber of Commerce no. 75699877, all rights reserved. For more information visit www.speeddy.com